






The Energizer HDL10 Headlamp is another innovative headlamp solution within the extensive headlamp line. Featuring bright, durable and energy efficient LED technology, users get a bright, lightweight, hands-free solution with ample run time capability. It is a perfect light for home, work and outdoor activities. With a comfortable, adjustable head strap and anti-glare pivoting head to direct light exactly as needed, this headlamp is another way *Energizer®* continues to deliver innovative lighting solutions.

Lumens	Runtime	Beam Distance	Drop	Water Ingress
 FL1 STANDARD 250 LUMENS	 FL1 STANDARD 7h	 FL1 STANDARD 60m	 FL1 STANDARD 1m	 FL1 STANDARD IPX4



BATTERY SPECIFICATIONS			
Battery Type	ENR Max Alkaline		
Battery Size	AAA		
Number of Cells	3		
BATTERY PERFORMANCE			
Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
High	250	7	60
Low	25	40	
Modes			
High, Low, Off			

DESIGN BENEFITS	
✓ Easy to use push button allows users to select high or low mode ✓ Compact, lightweight design – comfortable to wear. ✓ Water-resistant with shatterproof lens	
PERFORMANCE BENEFITS	
✓ Powerful white LEDs and a high/low setting to control light intensity provide good, all-round coverage for a variety of tasks and activities ✓ Up to 4X brighter than standard LED technology ✓ Durable, water-resistant design.	
LIGHT AND POWER SOURCE	
✓ Powerful white LEDs and a high/low setting to control light intensity provide good, all-round coverage for a variety of tasks and activities ✓ Up to 4X brighter than standard LED technology ✓ Operates on 3 AAA batteries ✓ CCT: 5000K CRI:75	
PRODUCT SPECIFICATIONS	
Weight:	57 Grams / 2.01 Ounces
Dimensions:	60 mm x 37 mm x 47 mm 2.36" x 1.46" x 1.85"
ELECTRICAL CHARACTERISTICS	
Nominal Power Consumption:	1.95 W
Batteries:	3 AAA Energizer E92 4.5V dc
LED Specifications:	LED 3.0V cc / 650 mA
DISCLAIMERS	
Tested according to ANSI FL1 Standards. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.	
CERTIFICATES AND COMPLIANCE	
EMC, EN62471, FCC	
  	

OPERATING INSTRUCTIONS

1. Press 1x for High
2. Press 2x for Low
3. Press again to turn off

BATTERY CHANGING INSTRUCTIONS

1. Release battery door locking tab by pulling upward and to the front.
2. Open battery door.
3. Load AAA batteries by the orientation shown in the battery cavity.
4. Close the battery door
5. Latch locking tab.