

## O-range ECON® 2 / 3 / 4 - gang junction boxes



### O-range ECON® 4 one-gang junction box, air-tight, Depth 48 mm, halogen-free

- Air-tight design with sealing membranes
- Toolless cable and conduit entries
- Integrated cable retention of the NYM cable, self-locking of the conduit
- Standardised separation of individual installation openings using a bridge
- Can be combined with all O-range® programme applications

LUFTDICHT



|                                                                  |                |
|------------------------------------------------------------------|----------------|
| <b>Article no:</b>                                               | <b>9254-78</b> |
| EAN:                                                             | 4013456550940  |
| For panel thickness                                              | 7 - 40 mm      |
| Depth                                                            | 48 mm          |
| Cut hole Ø                                                       | 4 x 68 mm      |
| Centre distance                                                  | 71 mm          |
| Device screws +/-                                                | 8              |
| Conduit entries up to Ø 20 mm                                    | 8              |
| Conduit entries up to Ø 25 mm                                    | 2              |
| Cable entries 3 x 2.5 mm <sup>2</sup> or 5 x 1.5 mm <sup>2</sup> | 2              |
| Cable entries 3 x 1.5 mm <sup>2</sup>                            | 4              |
| Halogen-free                                                     | Yes            |
| Number of bridges                                                | 2              |
| Number of installation device openings                           | 4              |
| Packaging inner/dispatch                                         | 5/50           |

With the new O-range ECON® 2 / 3 / 4 - gang junction boxes, KAISER offers the perfect basis and especially easy processing for the fitting of all standard installation accessories in multiple combinations. Thanks to their large installation opening without a central separation, it is easy to wire multiple devices together and even makes possible the use of pre-wired installation accessories. If different electrical circuits – e. g. for supply and communication connections – are used within a combination, the individual accessory installation spaces can be separated easily and in a standardised way.

- Easy installation of pre-wired accessories without spatial separation
- Maximum flexibility when fixing accessories, generous tolerance compensation
- Standardised separation of individual installation openings using a bridge
- Complete assembly and installation with just one screwdriver
- Can be combined with all O-range® programme applications

